Amendments to the Claims:

Please cancel claim 1, and amend claims 2, 3, 6-8, 10, 12 and 14 such that the claims herein read as follows.

Listing of Claims:

1. (Cancelled)

2. (Currently amended) A clock synchronization circuit for generating an output clock signal that is substantially in synchronization with a reference clock signal when in an in-synchronization state with a phase difference between the two clock signals of less than a predetermined value, the clock synchronization circuit comprising:

a programmable delay element coupled to the reference clock signal for introducing an adjustable delay in the reference clock signal to produce a delay-adjusted delayed output clock signal that becomes increasingly closer to being in synchronization with the reference clock signal; and

a phase detector coupled to the reference clock signal and the delay-adjusted delayed output clock signal for detecting the phase difference between the two clock signals and for generating an in-synchronization signal when the in-synchronization state is reached~~according to Claim 1;~~ wherein the in-synchronization signal is a pulse having a pulse width sufficient to interrupt a microprocessor.

3. (Currently amended) A clock synchronization circuit for generating an output clock signal that is substantially in synchronization with a reference clock signal when in an in-synchronization state with a phase difference between the two clock signals of less than a predetermined value, the clock synchronization circuit comprising:

a programmable delay element coupled to the reference clock signal for introducing an adjustable delay in the reference clock signal to produce a

delay-adjusted delayed output clock signal that becomes increasingly closer to being in synchronization with the reference clock signal; and

a phase detector coupled to the reference clock signal and the delay-adjusted delayed output clock signal for detecting the phase difference between the two clock signals and for generating an in-synchronization signal when the in-synchronization state is reached, ~~according to Claim 1; wherein~~ the phase detector ~~comprises:~~comprising:

a pulse generator that produces a pulse of variable width when the output clock signal approaches the in-synchronization state as the adjustable delay is increased; and

a latch that is triggered by the pulse to generate the in-synchronization signal when the width of the pulse reaches a pulse width Z required to trigger the latch.

4. (Original) A clock synchronization circuit according to Claim 3; wherein the latch is a D-type latch.

5. (Original) A clock synchronization circuit according to Claim 3; wherein the pulse generator comprises:

means for producing a window of a known width Y that is at least equal to the pulse width Z; and

means for generating a signal (IN1) from the delay-adjusted delayed output clock signal whose mark of a cycle is brought to overlap with the window when the adjustable delay is increased to produce the pulse.

6. (Currently amended) A clock synchronization circuit according to Claim 5; wherein the means for producing the window is a three-input AND gate having a first input coupled to the generated signal (IN1), wherein the generated signal is the reference clock signal delayed substantially by 2Y, a ~~first~~second input coupled to the reference clock signal, and a ~~second~~third input coupled to ~~an inverted~~the reference

clock signal that is inverted and delayed by Y ~~and the third input is coupled to the reference clock signal delayed substantially by 2Y.~~

7. (Currently amended) A clock synchronization circuit according to Claim 6; wherein the in-synchronization state is reached when the pulse width of the pulse generated by the pulse generator reaches a width Y-X that is equal to the pulse width Z; whereby the in-synchronization signal is generated, wherein X is a phase difference between the reference clock signal and the output clock signal.

8. (Currently amended) A clock synchronization circuit according to Claim 6; wherein the ~~second~~ third input of the three-input AND gate is coupled to ~~an inverted~~the reference clock signal that is inverted and delayed by $Y+D_1$ whereby D is a delay provided by a delay element.

9. (Original) A clock synchronization circuit according to Claim 8; wherein the bounds of the phase difference X is given by a worst case phase lead of Ymax-Zmin and a worst case phase lag of Ymin-Zmax depending on the values of Y and Z, wherein

Ymax and Ymin are the maximum and minimum delays of a NOT gate respectively; and

Zmax and Zmin are the maximum and minimum pulse widths required to trigger the latch respectively.

10. (Currently amended) A clock synchronization circuit according to Claim ~~1~~2; wherein the clock synchronization circuit is implemented in a programmable gate array.

11. (Original) A clock synchronization circuit according to Claim 8; wherein the delay-adjusted output clock signal is carried on a trace on a printed circuit board on which the programmable gate array is mounted.

12. (Currently amended) A method of generating a delayed output clock signal that is substantially in synchronization with a reference clock signal when the delayed output clock signal has a predetermined phase difference X with the reference clock signal, the method comprising:

inverting and delaying by a first delay the reference clock signal to produce an intermediate clock signal, wherein this intermediate clock signal cooperates with the reference clock signal to provide a window of width equal to the predetermined delay;

introducing an adjustable delay in the intermediate clock signal to produce a delay-adjusted delayed output clock signal;

inverting and delaying by a second predetermined delay Y the delay-adjusted delayed output clock signal to produce ~~a~~ the reference clock signal delayed by the first delay and the second predetermined delay Y;

increasing the adjustable delay to bring a cycle of the delay-adjusted delayed output clock signal to be increasingly in synchronization with a subsequent cycle of the reference clock signal until a synchronization condition is reached where a mark of a cycle of the reference clock signal delayed by the first delay and the second predetermined delay Y appears in the window to indicate that the delay-adjusted delayed output clock signal leads the reference clock signal by the phase difference X that is equal to the second predetermined delay Y.

13. (Original) A method according to Claim 12; wherein increasing the adjustable delay comprises increasing the adjustable delay by a known delay step D each time the adjustable delay is incremented.

14. (Currently amended) A method according to Claim 13; further comprising increasing the delay by a further number of delay steps corresponding to Y/D to bring the delay~~ed~~-adjusted delayed output clock signal to be more in synchronization with the reference clock signal after the synchronization condition is reached.

15. (Original) A method according to Claim 12; wherein increasing the adjustable delay comprises increasing the adjustable delay until a portion of the mark corresponding to a width of Z appears in the window; whereby the delay-adjusted delayed output clock signal leads the reference clock signal by a phase difference X that is equal to the second predetermined delay Y minus the width Z.

16. (Original) A method according to Claim 13; wherein Y is smaller than Z and the first delay is greater than Z and wherein increasing the adjustable delay comprises increasing the adjustable delay until a portion of the mark corresponding to a width of Z appears in the window; whereby the delay-adjusted delayed output clock signal lags the reference clock signal by a phase difference X that is equal to the width Z minus the second predetermined delay Y.